

CR18X series cylindrical capacitive sensor



Feature description

- Integrated housing matches double highlighted LED indicator
- IP67 protection class which is effectively moisture-proof and dust-proof
- The maximum operating voltage can be 40VDS which can effectively prevent the influence from power ripple
- Enhance detection distance. Sensitivity adjustment adopts multi-turn potentiometer so as to reach higher adjustment accuracy
- High reliability, excellent EMC design with protection against short circuit, overloaded and reverse polarity
- Widely used in both metal and non-metal (plastic, powder, liquid, etc.) material testing




Model specification				
NPN NO	CR18XCF08DNOY	PNP NO	CR18XCF08DPOY	
NPN NC	CR18XCF08DNCY	PNP NC	CR18XCF08DPCY	
NPN NO+NC	CR18XCF08DNRY	PNP NO+NC	CR18XCF08DPRY	

Specifications			
Installation type	Flush	Indicator	Output indication:Yellow LED;Power indicator:Green LED
Rated distance Sn	8mm [®]		Overload or short circuit indication:Yellow LED flashes
Ensure distance Sa	≤5.76mm	Switching frequency	25Hz
Adjust the distance	312mm	Ambient temperature	When working:-2570°C(No icing, No condensation)
Adjustment method	Multi-turn potentiometer		When storing:-3080°C(No icing, No condensation)
	(Electrical adjustment > 10)	Environment humidity	3595%RH(No icing, No condensation)
Standard test object	Fe 24*24*1t(Grounded) ²	Vibration resistant	1055Hz,Dual amplitude 1mm(2 hours
Supply voltage	1030VDC		each in X, Y, and Z directions)
Load current	≤200mA	Impulse withsand	30g/11ms,3 times each for X,Y,Z direction
Residual voltage	≤2V	High pressure resistant	1000V/AC 50/60Hz 60s
Consumption current	≤20mA	Insulation resistance	≥50MΩ(500VDC)
Switch point offset [%/Sn]	≤±10%	Shape specification	M18*1*70mm
Temperature drift [%/Sr]	≤±20%	Protection degree	IP67
Hysteresis range [%/Sr]	320%	Housing material	Nickel copper alloy
Repetitive error [R]	≤5%	Connection type	2m PVC Cable
Circuit protection	Short circuit protection, Overload protection,	Accessories	M18 nuts×2, Slotted screwdriver, Operation manual
	Reverse polarity protection		

Note: ①the factory default sensing distance is Sn±10%

②unit:mm



Wiring diagram

